## QuickHelp

# **Device Settings Features**

Use the bookmarks in the left-hand column to jump to the QuickHelp answers to these questions:

How do I set up the LightRing pattern, brightness and color? How do I set up the screensavers on my nVP2? How do I turn Video Center notifications on and off? How do I send SignMail alerts to one or two email addresses? How do I set up the Saved Text feature? How do I turn the Camera Notifications feature on and off?

### How do I set up the LightRing pattern, brightness and color?

Step 1. Start at the Home screen as shown below.



### Step 2. Select the Settings button to open the screen shown below.



### Step 3. Select the Device Options button to open the screen shown below.



The LightRing button will be selected when you first open the Device Options settings.

Step 4. To select a new default LightRing pattern, move to the list in the center of the screen as shown below.

	□ ● 差	🔅 Settings			(222) 444-	-9999
Single Chaser button highlighted	Device Options LightRing Sound Screen Controls Privacy/Notifications myPhone Bluetooth	What is my default LightRing pattern? Wipe Filled Wipe Flash Single Chaser Double Chaser Half Chaser Dark Chaser Pulse Alternate Flash Fill & Unfill Off / No pattern	What is What is	s my LightRin Medium s my default	(222) 444-	ess?

Step 5. For example, you could select the Double Chaser pattern as shown below.

	🙄 🏁 🖉	🗱 Settings	(222) 444-9999
Double Chaser button highlighted ————————————————————————————————————	Device Options LightRing Sound Screen Controls Privacy/Notifications myPhone Bluetooth	What is my default LightRing pattern? Wipe Filled Wipe Flash Single Chaser Double Chaser Half Chaser Dark Chaser Pulse Alternate Flash Fill & Unfill Off / No pattern	What is my LightRing brightness?   Medium +  What is my default LightRing color?

When you select a new pattern, the LightRing will flash with the new pattern. You can set the pattern and color for your individual contacts by editing the contact record.

Step 6. To select a new LightRing brightness, move to the control at the top-right corner of the screen as shown below.

	□ > 2	🔅 Settings	(222) 444-9999
LightRing brightness control highlighted	Device Options	What is my default LightRing pattern? Wipe Filled Wipe Flash	What is my LightRing brightness?
	LightRing		What is my default LightRing color?
	Sound	Single Chaser	
	Screen Controls	Double Chaser	
	Privacy/Notifications	Half Chaser Dark Chaser	
	myPhone	Pulse	
	Bluetooth	Alternate Flash Fill & Unfill	
		Off / No pattern	

You can choose from three levels of brightness: **Low**, **Medium** and **High**. The setting you choose will apply to all your incoming calls.

Step 7. To select a new default LightRing color, move to the control at the middle-right side of the screen as shown below.



When you select a new color, the LightRing will flash with the new color using the selected default pattern.

### How do I set up the screensavers on my nVP2?

### Step 1. Start at the Home screen as shown below.

	Today is Monday, 1:37 pm.				
		( ) -	★ Favorites		
	Call History	SignMail			
	2 Phone book	Video Center			
Settings button	Settings		🕎 📾 🍨 (222) 444-8888		

### Step 2. Select the Settings button to open the screen shown below.

		🗘 Set	tings	(222) 444-8888
	Call Options	Personal Info	C Support	
Device Options button	Device Options	Controls	Metwork/Admin	© Do not disturb About this device

Step 3. Select the Device Options button to open the screen shown below.

	11 🎽 2	🗱 Settings		(222	) 444-9999
	Device Options	what is my default LightRing pattern? W Wipe Filled Wipe Flash	What is my	LightRing bri	ghtness?
	LightRing		What is my default LightRing color?		
Screen Controls	Sound	Single Chaser			
button	Screen Controls	Double Chaser	•		
	Privacy/Notifications	Half Chaser Dark Chaser			
	myPhone	Pulse			
	Bluetooth	Alternate Flash Fill & Unfill			
		Off / No pattern			

Step 4. Move to the Screen Controls button to open the screen shown below.



### Step 5. To select a different screensaver, move to the screensaver control as shown below.



You can use the Screensaver controls to select a different screensaver. To see the available screensavers, use the controls to move up or down through the list.

### Step 6. For example, you could select the Winter Trees screensaver as shown below.

	□ >> 2	🔅 Settings	(222) 444-9999
Winter Trees screensaver selected	Device Options LightRing Sound Screen Controls Privacy/Notifications myPhone Bluetooth	What is my screensaver? Winter Trees + Play screensaver after 2 Minutes + Allow incoming calls to turn on TV? (Use TV CEC)	

Step 7. To change the time delay before the screensaver begins playing, move to the Play screensaver after control as shown below.

	□ ≫ ½	🛟 Settings	(222) 444-9999
	Device Options LightRing Sound Screen Controls Privacy/Notifications myPhone	What is my screensaver?	
3 minutes delay selected	Bluetooth	<ul> <li>Play screensaver after</li> <li>- 3 Minutes +</li> <li>Allow incoming calls to turn on TV? (Use TV CEC)</li> </ul>	

### How do I turn Video Center notifications on and off?

#### Step 1. Start at the Home screen as shown below.



### Step 2. Select the Settings button to open the screen shown below.

	· 》	🌣 Settings		(222) 444-9999
	Call Options	Personal Info	(?) Support	
Controls button	Device Options	Controls	Network/Admin	C Do not disturb About this device

Step 3. Select the Controls button to open the screen shown below.

	□ ≥ 2	🗘 Settings	(222) 444-9999
Tell me about new videos? checkbox	Controls General Directory Service	Call History Clear call history Phonebook Show contact photos? Turn on Spanish features? Video Center Tell me about new videos?	Play SignMail greeting after – 8 rings + Send me SignMail alerts?

Step 4. Move to the Tell me about new videos? checkbox as shown below.

	□ ∞ ½	🔅 Settings	(222) 444-9999
Tell me about new videos? checkbox without check	Controls General Directory Service	Call History Cear call history Phonebook Show contact photos? Turn on Spanish features? Video Center Tell me about new videos?	<ul> <li>Play SignMail greeting after</li> <li>8 rings +</li> <li>Send me SignMail alerts?</li> </ul>

When the **Tell me about new videos?** checkbox does *not* contains a check, you will not receive notifications that new videos are available for viewing in the Video Center.

### Step 5. Select the Tell me about new videos? checkbox to add a check as shown below.



When the **Tell me about new videos?** checkbox contains a check, you will receive notifications whenever new videos are available for viewing in the Video Center.

### How do I send SignMail alerts to one or two email addresses?

### Step 1. Start at the Home screen as shown below.



Step 2. Select the Settings button to open the screen shown below.

	· 》	🌣 Settings		(222) 444-9999
	Call Options	Personal Info	(?) Support	
Controls button	Device Options	Controls	Network/Admin	C Do not disturb About this device

Step 3. Select the Controls button to open the screen shown below.

	□ ≠ 2	🗘 Settings	(222) 444-9999
Send me SignMail alerts?	Controls	Call History	Play SignMail greeting after - 8 rings +
	Directory Service	Show contact photos? Turn on Spanish features? Video Center Tell me about new videos?	- Send the Signman dierts?

Step 4. Move to the Send me SignMail alerts? checkbox as shown below.

	11 🎽 🖉	🗱 Settings	(222) 444-9999
Send me SignMail alerts?	Controls	Call History	Play SignMail greeting after – 8 rings +
Checkbox without check	Directory Service	Show contact photos? Turn on Spanish features? Video Center Tell me about new videos?	Send me SignMail alerts?

When the **Send me SignMail alerts?** checkbox does *not* contains a check, you will not receive emails that tell you when have received new SignMail messages.

### Step 5. Select the Send me SignMail alerts? checkbox to add a check as shown below.

	E 🗱 🖉	🔅 Settings	(222) 444-9999
Sand ma SignMail alarta?	Controls	Call History	Play SignMail greeting after
checkbox with check	General	Phonebook	Send me SignMail alerts?
Email address fields	Directory Service	Show contact photos? Turn on Spanish features? Video Center	Send an alert to this email address
		Tell me about new videos?	Send an alert to this email address

When the **Send me SignMail alerts?** checkbox contains a check, you can receive emails that tell you when have received new SignMail messages. You can enter one or two email addresses in the fields that have appeared below the checkbox. You must enter at least one email address for the feature to work.

### Step 6. Move to the first Send an alert to this email address button as shown below.

	□ > 2	🗱 Settings	(222) 444-9999
Email address button —	Controls General Directory Service	Call History	Play SignMail greeting after - 8 rings + ✓ Send me SignMail alerts? Send an alert to this email address ✓ Edit Send an alert to this email address

Step 7. Select the Edit button to open the dialog shown below.

	🖾 🕬 🖉 🗘 Settings														
Email address field														•	Done
		1	2	3	4	5	6	7	8	9	0	•	×	•	Clear
		Q	W	E	R	т	γ	U	1	0	Р	#	%	+	=
		А	S	D	F	G	Н	J	К	L	:			-	١
		1		Z	Х	С	v	В	Ν	М	?	@	\$	&	1
		ABC	]^<			Sp	ace			,		1	;	_	1

You can use the on-screen keyboard to enter the email address. When you are finished, select the **Done** button to return to the *Controls* screen. Repeat the process for the second email address field if you want to have emails sent to two addresses when you receive new SignMail messages.

When you are finished making changes, return to the *Home* screen by pressing the **Home** key on the remote control. Your changes will be saved.

### How do I set up the Saved Text feature?

You can use the Saved Text feature to create and save up to 10 short text strings that you can quickly call up during an active videophone call to send using the Share feature.

Step 1. Start at the Home screen as shown below.



#### Step 2. Select the Settings button to open the screen shown below.

		🔅 Seti	tings	(222) 444-8888
Call Options button selected	Call Options	Personal Info	Support	
	Device Options	Controls	Network/Admin	C Do not disturb About this device

Step 3. Select the Call Options button to open the screen shown below.

🖸 参 🕬 差	🛱 Settings	(222) 444-9999
Call Options	<ul> <li>Turn on call waiting?</li> <li>Show a hint in my options bar when my call starts?</li> </ul>	
Saved Text	How long should I display my options bar?	
Voice Carry Over	– 6 seconds +	
VRS Announce		

Step 4. Select the Saved Text button to open the screen shown below.

	□ * ™ 差	🔅 Setti	<b>1gs</b> (222) 44	4-9999
	Call Options	Saved Text 1 My address is	Saved Text 6	
Saved Text button	In-call Options Saved Text	Saved Text 2	Saved Text 7	
	Voice Carry Over VRS Announce	Saved Text 3	Saved Text 8	
Saved Text 1 through 10 fields		Saved Text 4	Saved Text 9	
		Saved Text 5	Saved Text 10	

In this example, one Saved Text item (Saved Text 1) has already be created and saved.

### Step 5. Move to the Saved Text 2 field to reveal the Edit button as shown below.

	■ * ≫ ½	🗘 Settings	(222) 444-9999
	Call Options	Saved Text 1 My address is	Saved Text 6
Saved Text 2 Edit button	In-call Options Saved Text Voice Carry Over	Saved Text 2 Saved Text 3	Saved Text 7 Saved Text 8
	VRS Announce	Saved Text 4	Saved Text 9
		Saved Text 5	Saved Text 10

#### Step 6. Select the Saved Text 2 Edit button to open the dialog shown below.

Enter text to be saved here													•	Done
	1	2	3	4	5	6	7	8	9	0	•		•	Clear
	Q	W	E	R	т	Y	U	Т	0	Р	#	%	+	=
	А	S	D	F	G	Н	J	К	L	:	"	1	-	١
	4		Z	Х	С	V	В	Ν	М	?	@	\$	&	1
	ABO	C>^[			Spa	ace			,		1	;	_	1

### Step 7. Use the on-screen keyboard to enter the text you want to save as shown below.

	<b>0</b> *	54. ž.)				33	‡ Se	tting	5				(222) 4	4-9999
	Му	ассо	unt r	numb	er is.									Done
	1	2	3	4	5	6	7	8	9	0				ar
one button	q	w	е	r	t	у	u	T	0	р	#	%	+	=
	а	s	d	f	g	h	j	k	l	:		1	-	١
	1	Þ.	z	x	с	v	b	n	m	?	@	\$	&	/
	ABO	C>^[			Sp	ace			,		1	;	-	1

### Step 8. When finished, select the Done button to return to the screen shown below.

	😪 Settings	(222) 444-9999
Call Options	Saved Text 1	Saved Text 6
	My address is	
In-call Options	Saved Text 2	Saved Text 7
Saved Text	My account numbe 🔗 Edit	
Voice Carry Over	Saved Text 3	Saved Text 8
VRS Announce		
	Saved Text 4	Saved Text 9
	Saved Text 5	Saved Text 10

### Step 9. Repeat Steps 5 through 7 if you want to create more Saved Text items.

### How do I turn the Camera Notifications feature on and off?

### Step 1. Start at the Home screen as shown below.



Step 2. Select the Settings button to open the screen shown below.

		🔅 Settings		(222) 444-8888
	<b>C</b> all Options	Personal Info	(?) Support	
Device Options button	Device Options	Controls	Network/Admin	C Do not disturb About this device

Step 3. Select the Device Options button to open the screen shown below.

	🗘 Settings			(222)	444-8888
Device Options	What is my default LightRing pattern?	What	is my LightRi	ng brig	htness?
	Wipe	-	Medium	+	
LightRing	Flash	What	is my default	LightR	ing color?
Sound	Single Chaser				
TV Display	Double Chaser	•		•	•
Dalua au (Natificationa	Half Chaser				
Privacy/Notifications	Dark Chaser				
myPhone	Pulse				
Bluetooth	Alternate Flash				
	Fill & Unfill				
	Off / No pattern				

Step 4. Move to the Privacy/Notifications button as shown below.

	<b>•</b>	🗘 Settings	(222) 444-8888
Privacy/Notifications button	Device Options LightRing Sound TV Display Privacy/Notifications myPhone Bluetooth	<ul> <li>Always answer calls in Privacy mode?</li> <li>Hide my caller ID?</li> <li>Don't accept anonymous calls?</li> </ul> Camera notifications <ul> <li>Don't show SignMail and Missed Call LED notifications?</li> </ul>	

	🖂 🏁 Ž	🗘 Settings	(222) 444-9999
Don't show SignMail and Missed Call LED notifications? checkbox without check	Device Options LightRing Sound Screen Controls Privacy/Notification myPhone Bluetooth	<ul> <li>Always answer calls in Privacy mode?</li> <li>Hide my caller ID?</li> <li>Don't accept anonymous videophone calls?</li> <li>Camera notifications</li> <li>Don't show SignMail and Missed Call LED notifications?</li> </ul>	

When the **Don't show SignMail and Missed Call LED notifications?** checkbox does *not* contains a check, the LED lights on the remote camera unit will not light up to indicate you have received new SignMail and/or missed calls.

Step 6. Select the Don't show SignMail and Missed Call LED notifications? checkbox to add a check as shown below.

	□ ≠ 2	🛟 Settings	(222) 444-9999
Don't show SignMail and Missed Call LED notifications? checkbox with check	Device Options LightRing Sound Screen Controls Privecy/Notification myPhone Bluetooth	<ul> <li>Always answer calls in Privacy mode?</li> <li>Hide my caller ID?</li> <li>Don't accept anonymous videophone calls?</li> <li>Camera notifications</li> <li>On't show SignMail and Missed Call LED notifications?</li> </ul>	

When the **Don't show SignMail and Missed Call LED notifications?** checkbox contains a check, the LED lights on the remote camera unit will light up to indicate you have received new SignMail and/or missed calls.